protectline
powered by tuncmatik

REGULINE Servo

REGULATOR

REGULINE

Single Phase 10kVA-15kVA-20kVA

Three Phase 10kVA-15kVA-20kVA-30kVA

- Automatic voltage regulation
- Wide Voltage Range
- CPU controlled
- Servo motor
- Digital voltage indicator
- Low/High Voltage protection
- Selectable delay time
- Compact design
- Widely used (Combi boilers, TV, PC, home and office applications)

tuncmatikgroup
power solutions

ISO 9001 Registered
ISO 14001 Registered
OHSAS 18001 Registered

tuncmatik
www.tuncmatik.com pure power

tuncmatik REGULINE REGÜLATÖR

Single Phase 10000VA-15000VA-20000VA/Three Phase 10000VA-15000VA-20000VA-30000VA

Tunçmatik
International Enerji Çözümleri
Sanayi ve Ticaret A.Ş.

Head Office
Yenişehir Mahallesi
İmar İskan Caddesi No: 3
34779 Ataşehir/İstanbul-Turkey
phone : +90.216.415.04.97
fax : +90.216.420.35.29

export@tuncmatik.com

GREEN ENERGY

tuncmatik products offer energy savings of up to 30%, helping you consume less of a dwindling resource.

MODEL		INPUT		OUTPUT				DIMENSIONS	WEIGHT
		Voltage	Frequency	Voltage	Frequency	Power	Max. Current	H x W x D	Kg.
Single Phase	10 kVA 15 kVA 20 kVA	140-250V	50 Hz	220V± %1-3	50 Hz	10000VA 15000VA 20000VA	45 A 68 A 90 A	490x420x450 490x420x590 490x420x590	39 47 60
Three Phase	10 kVA 15 kVA 20 kVA 30 kVA	300-430V		380V± %3		10000VA 15000VA 20000VA 30000VA	15 A 22 A 30 A 45 A	490x420x720 490x420x720 490x420x800 490x420x900	48 55 82 100